

# WLB92 Industrial LED Light Bar (DC)



## Datasheet

Banner's WLB92 is a very bright LED fixture/luminaire that features an even light output for a no glare 'glow'. The WLB92 series is designed for a wide variety of environments and applications, including but not limited to work stations, machine lighting, and low bay lighting. The WLB92 uses advanced LED lighting technology to provide a high-quality and maintenance free industrial lighting solution.

- Increase worker productivity and ergonomics with bright, high-quality, uniform light
- Exceptionally energy efficient for overall cost savings
- Durable light stands up to your environment with a rugged metal housing and shatter-resistant window
- Easy installation with surface mount brackets or a choice of snap, swivel, or hanging brackets
- Intensity can be controlled from 0 to 100% using Pulse Width Modulation (PWM) dimming
- Rated for use at 24 V dc



WLB92 Industrial LED Light Bars are available in several configurations including different lengths, switches, dimming capabilities, and cord options. See [Accessories](#) on page 5.




For PWM dimming, use with the LC65 Dimmer Module. For more information, refer to the LC65 LED Dimmer Module datasheet, p/n [177086](#).

Models	Lighted Length (mm)	Lighting Control	Connector	Lumens
WLB92X550PBQ	550	On/Off Switch, Dimming Knob	4-pin M12 Quick Disconnect (QD) Fitting <sup>1</sup>	3130
WLB92X1100PBQ	1100			6500
WLB92X550PWMQ	550	No Switch, PWM Dimming		3130
WLB92X1100PWMQ	1100			6500
WLB92X550PB	550	On/Off Switch, Dimming Knob	2 m (6.5 ft) Cable	3130
WLB92X1100PB	1100			6500
WLB92X550PWM	550	No Switch, PWM Dimming		3130
WLB92X1100PWM	1100			6500

<sup>1</sup> Models with a quick disconnect fitting require a mating cordset.





## Specifications

### Supply Voltage

Operating Voltage: 24 V dc ( $\pm 10\%$ )  
Use only with a suitable Class 2 power supply. (North America)  
Use only with a suitable Class III SELV power supply. (Europe)

### Supply Current

Lighted Length (mm)	Max Current Draw (A)	Typical Current Draw at 24 V dc (A)
550	1.75	1.45
1100	3.50	2.90

### Supply Protection Circuitry

Protected against reverse polarity and transient voltages

### Light Characteristics

Color: Daylight White  
Color Temperature (CCT): 5000K ( $\pm 300K$ )  
Lumen Output: 550 mm - 3130 lumens, 1100 mm - 6500 lumens  
Luminous Efficacy: 92 lumens/watt typical at 24 V dc at 25 °C (77 °F)  
CRI: 82, typical

### LED Lifetime

Lumen Maintenance -  $L_{70}$   
When operating within specifications, output will decrease less than 30% after 50,000 hours.

### Test Data

LM-79, LM-80, TM-21

### Certifications



**CAUTION:** To Reduce the Risk of Fire. Do not install the 550 mm models in a compartment smaller than 305 mm by 305 mm by 675 mm. Do not install the 1100 mm models in a compartment smaller than 305 mm by 305 mm by 1350 mm.

### Switch/Dimming Knob (some models)

On/Off Switch and dimming knob, dimmable to 0% intensity

### Pulse Width Modulation (PWM) Dimming (some models)

Frequency: Up to 1000 Hz  
Voltage: 12 to 24 V dc  
Current: 4 mA maximum  
Compatible with the LC65 Dimmer Module. For more information, refer to the LC65 LED Dimmer Module datasheet, p/n [177086](#).

### Construction

Anodized aluminum housing, polycarbonate window and end caps, and stainless steel mounting brackets

### Spacing Criterion

Vertical: 1.20  
Horizontal: 1.32

### Mounting

Surface mount brackets included (2)  
Compatible with integral 45 mm aluminum framing mounting slots  
Several optional mounting brackets available (see [Accessories](#) on page 5)

### Connections

Integral 4-pin M12/Euro-style quick disconnect connector (4-pin connecting cordset required for QD models); or 2 m (6.5 ft) integral cable

### Environmental Rating

IEC IP40

### Operating Temperature

-40 °C to +70 °C (-40 °F to +158 °F)  
550 Lighted Length Models: Light output begins to decrease above 65 °C (149 °F); light output is approximately 90% of maximum intensity at 70 °C (158 °F).  
1100 Lighted Length Models: Light output begins to decrease above 45 °C (113 °F); light output is approximately 75% of maximum intensity at 60 °C (140 °F) and 65% of maximum intensity at 70 °C (158 °F).

### Storage Temperature

-40 °C to +70 °C (-40 °F to +158 °F)

### Vibration and Mechanical Shock

Vibration 10 to 55 Hz 0.5 mm p-p amplitude per IEC60068-2-6  
Shock 5G 11 ms duration, half sine wave per IEC60068-2-27

## Spacing Criteria (SC)

The spacing criteria is the fixture-spacing-to-mounting-height ratio and aids in laying out a pattern of fixtures. Multiply the spacing criteria by the mounting height to get the maximum fixture spacing that still provides even illumination (no shadowing between fixtures).

Luminaire Spacing = SC  $\times$  Height to Illuminated Plane

The mounting height is the distance from the fixture to the surface you are lighting.

## Light Characteristics




Figure 1. 550 mm Models





Figure 2. 1100 mm Models

## Dimensions



Model	L1	L2
WLB92X550..Q	542 mm (21.3 in)	650 mm (25.6 in)
WLB92X1100..Q	1097 mm (43.2 in)	1205 mm (47.4 in)
WLB92X550..	542 mm (21.3 in)	650 mm (25.6 in)




Model	L1	L2
WLB92X1100..	1097 mm (43.2 in)	1205 mm (47.4 in)



## Wiring Diagram




	Pin	Wire Color	Connection
	1	brown	24 V dc
	3	blue	dc common
	4	black	Pulse width modulation (PWM) input (PWM models only)
	2	white	Not used

For maximum intensity, leave the black wire floating or connected to common. There is no black wire present in the models with a dimming knob.

## Accessories

4-Pin Threaded M12/Euro-Style Cordsets (15 ft and Shorter)				
Model	Length	Style	Dimensions	Pinout (Female)
MQDC-406	1.83 m (6 ft)	Straight		  1 = Brown 2 = White 3 = Blue 4 = Black
MQDC-415	4.57 m (15 ft)			
MQDC-406RA	1.83 m (6 ft)	Right-Angle		
MQDC-415RA	4.57 m (15 ft)			

Brackets	
<p><b>LMBWLB92</b></p> <ul style="list-style-type: none"> <li>Standard bracket that ships with the WLB92 light</li> <li>Stainless steel</li> <li>Includes two surface mount brackets, four screws, and four t-nuts</li> </ul> 	<p><b>LMBWLB92CLIP</b></p> <ul style="list-style-type: none"> <li>Snap clip allows for tool-less installation</li> <li>Stainless steel</li> <li>Includes four snap clips, four screws, and two insulator caps</li> </ul> 

Brackets	
<p>LMBWLB92HK5</p> <ul style="list-style-type: none"><li>• Hanging bracket kit allows for suspended installation</li><li>• Includes two hanging bracket assemblies, four screws, four t-nuts, and two 15-24 mm cables</li></ul> 	<p>LMBWLB92RAS</p> <ul style="list-style-type: none"><li>• Swivel brackets allow for 180° of movement in seven fixed positions</li><li>• Stainless steel</li><li>• Includes two swivel bracket assemblies, eight screws, and four t-nuts</li></ul> 
<p>LMBWLB92S</p> <ul style="list-style-type: none"><li>• Surface mount brackets allow for mounting at the end of the light</li><li>• Stainless steel</li><li>• Includes two end brackets, four screws, and four t-nuts</li></ul> 	

## FCC Part 15 and CAN ICES-3 (B)/NMB-3(B)

This device complies with part 15 of the FCC Rules and CAN ICES-3 (B)/NMB-3(B). Operation is subject to the following two conditions:

1. This device may not cause harmful interference, and
2. This device must accept any interference received, including interference that may cause undesired operation.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules and CAN ICES-3 (B)/NMB-3(B). These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the manufacturer.

## Banner Engineering Corp. Limited Warranty

Banner Engineering Corp. warrants its products to be free from defects in material and workmanship for one year following the date of shipment. Banner Engineering Corp. will repair or replace, free of charge, any product of its manufacture which, at the time it is returned to the factory, is found to have been defective during the warranty period. This warranty does not cover damage or liability for misuse, abuse, or the improper application or installation of the Banner product.

THIS LIMITED WARRANTY IS EXCLUSIVE AND IN LIEU OF ALL OTHER WARRANTIES WHETHER EXPRESS OR IMPLIED (INCLUDING, WITHOUT LIMITATION, ANY WARRANTY OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE), AND WHETHER ARISING UNDER COURSE OF PERFORMANCE, COURSE OF DEALING OR TRADE USAGE.

This Warranty is exclusive and limited to repair or, at the discretion of Banner Engineering Corp., replacement. IN NO EVENT SHALL BANNER ENGINEERING CORP. BE LIABLE TO BUYER OR ANY OTHER PERSON OR ENTITY FOR ANY EXTRA COSTS, EXPENSES, LOSSES, LOSS OF PROFITS, OR ANY INCIDENTAL, CONSEQUENTIAL OR SPECIAL DAMAGES RESULTING FROM ANY PRODUCT DEFECT OR FROM THE USE OR INABILITY TO USE THE PRODUCT, WHETHER ARISING IN CONTRACT OR WARRANTY, STATUTE, TORT, STRICT LIABILITY, NEGLIGENCE, OR OTHERWISE.

Banner Engineering Corp. reserves the right to change, modify or improve the design of the product without assuming any obligations or liabilities relating to any product previously manufactured by Banner Engineering Corp.